

Installation instructions : SY9026WW or NW ARC Side Lit LED Strip


Thank you for purchasing this SycamoreLED.com product. When installed correctly this product will provide years of use. For technical support or warranty information please visit www.sycamoreLED.com, or call our dedicated technical helpline +44 (0) 113 2866686.

IMPORTANT—Please read prior to installation

- 1) Please read these instructions carefully before commencing any work
- 2) Please retain these instructions for future reference
- 3) It is strongly recommended that this unit is installed by a qualified electrician in accordance with the IEE wiring regulations and building regulations
- 4) To prevent electrocution switch the power off at the mains supply before installing or maintaining this fitting
- 5) Ensure others cannot restore the electrical supply without your knowledge
- 6) The PSU must be 12Vdc rated and compatible with the pre-wired connector system of this product
- 7) Locate driver (IP20) in an unclassified zone
- 8) Never exceed the wattage stated

SPECIFICATION & DIAGRAMS

THE TECHNICAL SPEC...	
Fitting Type	LED
Voltage	12Vdc
Colour Temperature	Warm White (3000k) Natural White (4000k)
Wattage	1.5W per metre
IP Rating	IP67
Guarantee Period	3 Years*
Cut marks	Every 25mm
LED's per metre	360



INSTALLATION INSTRUCTIONS


IDEAL FOR USE IN WORKTOPS, GOLA PROFILE , & PLINTH LIGHTING


- 1) **IMPORTANT:** Before installation of any LED strip, the surface to which it is being installed upon must be cleaned with white spirit or similar to ensure adhesion.
- 2) Flexible LED strip can be installed by the VHB tape, or by fitting into an aluminium extrusion.
- 3) This strip will bend around 90 degree in the vertical plane.
- 4) The strip is pre-wired with a 2M cable and connector at each end to allow any cut of pieces to be re-used
- 5) The strip cannot be twisted, dropped or left hanging
- 6) The strip can be cut at 25mm marked intervals
- 7) Locate in desired location and make sure that each cable/connector can connect to a relevant PSU (12Vdc)
- 8) Ensure the strip is secure along its length
- 9) Restore power and test operation.

CARE IN USE


- 1) Please note this fitting has non replaceable parts
- 2) Always switch off or disconnect from the mains when cleaning the product.
- 3) We recommend cleaning with a soft dry cloth. Do not use scourers, abrasives or chemical cleaners.
- 4) Do not allow moisture to come into contact with electrical parts
- 5) This luminaire should not be disposed of with normal household rubbish. When a replacement is purchased, this luminaire should be returned to the retailer to safely dispose of (WEEE Directive effective July 2006—Waste from Electrical & Electronic Equipment)

SycamoreLED.
com SY9026

 This luminaire contains built-in LED lamps.

 } LED

The lamps cannot be changed in the luminaire.

874/2012 

Download instructions



 **EnabLED**
Licensing Program for LED
Luminaires and Retrofit Bulbs

Member
Sycamore Lighting
Limited

