

Installation instructions : Touch Dimming Control Switch SY7917

Thank you for purchasing this SycamoreLED.com product. Please make sure instructions are followed carefully prior to and during installation and product is not altered, otherwise warranty may not be valid. For technical support or warranty information please visit www.sycamoreLED.com, or call our dedicated technical helpline +44 (0) 113 2866686.

IMPORTANT—Please read prior to installation

- 1) Please read these instructions carefully before commencing any work
- 2) This product must be installed by a qualified electrician in accordance with the current IEE wiring regulations
- 3) To prevent electrocution switch the power off at the mains supply before installing or maintaining this fitting
- 4) Ensure others cannot restore the electrical supply without your knowledge
- 5) The PSU must be rated 12VDC and be compatible with the pre-wired connector system of this product
- 6) Never exceed the wattage stated

INSTALLATION & OPERATION

- 1) Position switch in desired location and use adhesive pad supplied to ensure the switch is lined up square.
- 2) Remove front cover and use the 2 screws to secure the body in position.
- 3) Replace front cover.
- 4) Connect switch to a 12vdc supply via plug and outgoing lights can then be connected via a distribution block (multiple lights) by the outgoing female connector.
- 5) When 12v supply is switched on there is a blue light to indicate that power is on to the switch. Press icon until desired lighting level is achieved.
- 6) To switch off quickly press icon.
- 7) To switch back on, again quickly press the icon and the light will come on at the brightness level at which they were switched off.
- 8) Brightness can then be adjusted by long pressing the icon.

