



FEATURES

This motion sensor, which is a special version suitable for installation in ceilings can be used to automatically switch lights on and off, by detecting movement. This sensor can be used with LED, halogen & fluorescent light sources.

The unit also features an adjustable timer, which can be set from 30 seconds, up to 30 minutes. The unit also has photocell adjustment, so you can adjust the lux level sensor by 10—2000 lux.

TECHNICAL DATA

- Sensor distance seated—4m
- Sensor distance walking across—10m
- Sensor distance walking towards—6m
- IP20 rated
- Detector dimensions 36mm dia x 28mm (h)
- Power supply dimensions 165mm (l) x 24mm (w) x 24mm (h)
- Sensor range 360 degree
- 30 sec—30 min adjustment
- 10—2000 lux adjustment



Part Numbers	Description
SY7262A	Motion Sensor with adjustable timer and lux level
SY7561	Silver cover for motion sensor