

## Installation instructions : Dimmable Flexible LED Wall Bedside Light SY7307

Thank you for purchasing this SycamoreLED.com product. Please make sure instructions are followed carefully prior to and during installation and product is not altered, otherwise warranty may not be valid. For technical support or warranty information please visit [www.sycamoreLED.com](http://www.sycamoreLED.com), or call our dedicated technical helpline +44 (0) 113 2866686.

### IMPORTANT—Please read prior to installation

- 1) Please read these instructions carefully before commencing any work
- 2) This product must be installed by a qualified electrician in accordance with the current IEE wiring regulations
- 3) To prevent electrocution switch the power off at the mains supply before installing or maintaining this fitting
- 4) Ensure others cannot restore the electrical supply without your knowledge

### GENERAL

- 1) This fitting must be earthed
- 2) This fitting is dimmable
- 3) 3W IP20
- 4) 4000k

### INSTALLATION

- 1) Remove mounting plate from switch unit by twisting until keyways are aligned.
- 2) Lift plate from body of unit.
- 3) Secure mounting plate in desired location ensuring that the unit can be connected to a suitable electrical supply.
- 4) Connect live neutral and earth cables from unit to the electrical supply cable using connector strip supplied in pack.
- 5) Fit switch unit back onto plate by locating keyways on both plate and unit and twisting clockwise.
- 6) Once locked into the upright position, fix with securing screw in the bottom of the switch unit.
- 7) Restore power and check dimming operation.

### CARE IN USE

- 1) Please note this fitting has non replaceable parts
- 2) Always switch off or disconnect from the mains when cleaning the product.
- 3) We recommend cleaning with a soft dry cloth. Do not use scourers, abrasives or chemical cleaners.

sycamore SY7307



This luminaire contains built-in LED lamps.



} LED

The lamps cannot be changed in the luminaire.

874/2012

