

Installation instructions : 15MM ROUND LED PLINTH LIGHTS SY9936/SY9928A/SY9937

Thank you for purchasing this SycamoreLED.com product. Please make sure instructions are followed carefully prior to and during installation and product is not altered, otherwise warranty may not be valid. For technical support or warranty information please visit www.sycamoreLED.com, or call our dedicated technical helpline +44 (0) 113 2866686.

IMPORTANT—Please read prior to installation

- 1) Please read these instructions carefully before commencing any work
- 2) This product must be installed by a qualified electrician in accordance with the current IEE wiring regulations
- 3) To prevent electrocution switch the power off at the mains supply before installing or maintaining this fitting
- 4) Ensure others cannot restore the electrical supply without your knowledge
- 5) The PSU must be rated 12VDC and be compatible with the pre-wired connector system of this product
- 6) Never exceed the wattage stated

GENERAL

Item	Rated voltage/V	Rated power/W	LED numbers	IP Rating	Protection
SY9936	12v DC	1x 0.2w	1	67	CLASS 2

PRE—INSTALLATION

- 1) Prepare all the parts and tools required for the installation
- 2) Turn off power before installation.
- 3) If there is any damage on the housing or glass diffuser do not use it.

INSTALLATION

- 1) Cut a diameter hole to 10mm on the surface to which the light is being installed.
- 2) Put the wire through the hole, and connect to the ongoing lights using the plug in system. Repeat for follow on lights
- 3) Push the lamp into the hole and secure using the locking nut on the barrel.
- 4) Ensure the body of the lamp is securely fixed on the face of installation, then restore the power and check operation.

CARE IN USE

- 1) Please note this fitting has non replaceable parts
- 2) Always switch off or disconnect from the mains when cleaning the product.
- 3) We recommend cleaning with a soft dry cloth. Do not use scourers, abrasives or chemical cleaners.

sycamore SY9936/9928/9937



This luminaire contains built-in LED lamps.



} LED

The lamps cannot be changed in the luminaire.

874/2012

